



2229 DC-136  
CODE MX#1600207



Il DC-136 con 136 canali DMX è la massima espressione del controllo ibrido 2 in 1 che consente di utilizzare e programmare la sezione delle teste mobili o scanner, utilizza 128 canali DMX, e la sezione di "Par", 8 canali DMX, o gli effetti (ad esempio la macchina del fumo controllata in 0-10V o DMX) in due differenti Chase. Grazie a questa divisione nel controller stesso si ha poi la possibilità di avere il controllo indipendente dello Speed e del "Fade Time" per ogni sezione, pur avendo un Master e "Full On" generale. Una caratteristica di questa unità di controllo, che si differenzia anche dagli altri è la capacità di personalizzare l'uscita del segnale per ogni fader di ogni Fixtures. Per esempio nei controller standard abiliando Fixtures 1 attivi i canali DMX da 1 a 16 in ordine con il DC-136 si può impostare che dal Fader 1 corrisponda in uscita il canale DMX numero 3, il 2 al canale 7, 3 al canale 1, e così via.

#### SEZIONE "TESTEMOBILI", SPECIFICHE

- 8 Fixtures da 16 canali ciascuno
- 96 scene programmabili
- 8 Chase programmabili
- 8 gruppi Fixture assegnabili

#### SEZIONE PAR, SPECIFICHE:

- 8 fader dimmer
- Utilizzabile in combinazione con il DDP/DSP-405, UP-1 / UP-2 o di qualsiasi Dimmer/switching DMX
- 96 scene programmabili
- 6 Chase programmabili
- Par con Master e Fader

#### CARATTERISTICHE AGGIUNTIVE CONTROLLER

- Luminoso display LCD.
- Compact Flash (CF) card slot per scambiare dati, library, memoria e set-up dei file
- Funzione con microfono all'interno per il sincrono
- Joystick per il Pan / Tilt e pulsante Fine Pan / Tilt
- Toccare il pulsante Sync per la velocità / fade override
- Funzioni Step/ Mix/ Sequenza per esecuzioni show
- Pulsante Macchina fumo a switching
- Interruttore di polarità (2 -, 3 +, / 2 +, 3 -)
- Connettore DMX out 3poli
- Ingresso Midi
- Controller adattabile a rack
- Alimentazione: 230V / 9-15V DC, 500mA. (Incluso)
- Dimensioni: 670x300x150mm (occupa 4U rack)
- Peso: 4,9 kg
- Accessori opzionali: 32MB Compact Flash Card (Codice: 11271)



The DC-136 with 136 channels DMX is the ultimate expression of the hybrid control 2 in 1 which allows you to use and store the section of the moving heads or scanners, takes 128 DMX channels, and the section of "Par", 8 channels DMX or effects (eg smoke machine in a controlled 0-10V or DMX) in two different chase. Thanks to this division in the same controller then has the opportunity to have independent control of Speed and Fade Time for each section despite having a Masters and "Full On" General. A feature of this control unit, which also differs from the others is the ability to customize the out signal for each fader of each Fixtures. For example in the standard ECU abiliando Fixtures number 1 active DMX channels from 1 to 16 in order with the DC-136 can match the Fader 1 to channel output DMX 3, the 2 to channel 7, the 3 to channel 1, and so on.

#### MOVING LIGHT SECTION FEATURES

- 8 fixtures up to 16 channels each
- 96 programmable Scenes
- 8 programmable Shows
- 8 assignable Fixture Groups

#### PAR CAN DIMMER SECTION FEATURES

- 8 dimmer faders
- Use in conjunction with the DDP/DSP-405, UP-1/ UP-2 or any Dimmer DMX
- 96 programmable scenes
- 6 programmable shows
- Par Can Master fader
- assigned to all 8 Par Can channels

#### ADDITIONAL CONTROLLER FEATURES

- Bright LCD display.
- Compact flash (CF) card slot to exchange data, library, memory and set-up files
- Built in microphone for music sync functions
- Joystick for Pan / Tilt and button Fine Pan/ Tilt control of moving lights
- Tap Sync button for speed / fade override
- Step/Mix/Sequence function for shows
- Fog Machine trigger button
- Polarity switch (2-, 3+, / 2+, 3-)
- One DMX 3-pin XLR output
- Midi input
- Controller comes Tabletop Style
- includes removable rubber rails to fit standard 19"
- Power supply: 230V / 9-15V DC, 500mA. (Included)
- Dimensions: 670x300x150mm (Occupies 4U rack)
- Weight: 4,9 kg
- Optional accessory: 1GB Compact Flash Card (special version) code: 11271

| DATI TECNICI       | TECHNICAL DATA   |
|--------------------|------------------|
| Dimensioni (LxAxP) | 482 x 178 x 80mm |
| Peso               | 4,0kg            |

| ACCESSORI / | ACCESSORIES  |
|-------------|--------------|
| Code 11271  | 32MB CF Card |